## SEQLED E 138 **EMERGENCY LIGHT**

SeqLED E 138

SeqLED E 138 is an elegant and functional non-maintained emergency light for indoor installation. Luminaire for anti-panic is used in big, open areas with large mounting heights.

SeqLED E 138 suits perfect for areas with large mountings heights like shopping centers, warehouses, sport halls, foyers and cinemas.

The luminaire is designed for both new building construction and renovation of existing facilities. This can be used wall mounting





Potential free contacts




## **FEATURES AND BENEFITS**

- LED based non-maintained
- Delivered as self-contained/auto test luminaire
- Choice of 1, 3 or 8 hour autonomy via DIP switch
- Greater spacing with new efficient LED
- High lumen output 1h = 280lm, 3h = 120lm, 8h = 50lm
- IP65 dust and waterproof luminaire
- Technical lifetime of LED > 100 000 hours
- Simple and quick assembly and maintenance







## **SEQUED E 138 EMERGENCY LIGHT**

TECHNICAL DATA	
Reading distance, exit sign	-
Voltage	220-240VAC / 50-60Hz
Power consumption	4.8W / 5VA
Battery	4.8V/1Ah Li <sub>4</sub> Ti <sub>5</sub> O <sub>12</sub>
Battery protection	Over charge protection /full discharge protection
Charging Time	16 hours
Battery back-up time	1 hour / 3 hours / 8 hours (from dip switch)
Light source	1 white power LED
Technical lifetime (light source)	>100 000 hours
Lumen output, mains	-
Lumen output, emergency (1h / 3h / 8h)	280/120/50 lm
Approvals	EN 60598-1, EN 60598-2-22, EN 55015, EN 61547, EN 61000-3-2, EN 61000-3-3
Ambient temperature	-25 to 40 °C
Humidity	Up to 95%
IK rating	IK10
IP rating	IP20
Dimensions	160 x 160 x 55 mm
Weight	618 / 760 gr
Colour	White
Materials	PC, ABS/PC
Mounting method	Wall mounting

MODEL NO	DESCRIPTION	
138005	SeqLED E NM ST LED 230V 138h	
290BAT.5	Battery 4.8V/ 1Ah Li4Ti5012	
290099	Plug-in module potential free	

## For more information,

https://honeywellbuildings.in Call: 1-800-103-0339 Email: HBT-Indiabuildings@honeywell.com

Honeywell HBT India Buildings Unitech Trade Center, 5th Floor, Sector-43, Block C, Sushant Lok Phase - I, Gurgaon - 122 002



SEQLED E 138 EMERGENCY LIGHT